









Model Number

UB250-F77-E2-V31


Ultrasonic direct detection sensor

Features

- Miniature design
- Program input
- Degree of protection IP67
- Switching status indicator, yellow I FD

Diagrams

Characteristic response curve





Technical data

General specifications	
Sensing range	20 250 mm
Adjustment range	45 250 mm
Dead band	0 20 mm
Standard target plate	20 mm x 20 mm
Transducer frequency	approx. 400 kHz
Manada at antima	

Nominal ratings

Time delay before availability t_v ≤ 150 ms

Limit data

Permissible cable length max. 300 m

Indicators/operating means LED yellow

Electrical specifications

Rated operating voltage $\rm U_{\rm e}$ 24 V DC Operating voltage $\rm U_{\rm B}$ 20 ... 30 V DC , ripple 10 $\%_{\rm SS}$; 12 ... 20 V DC sensitivity

Input

Input type 1 program input

Level low level : 0 ... 0.7 V (Teach-In active)

high level : U_B or open input (Teach-In inactive)

switching state and flashing: Teach-In

 $\begin{array}{ll} \text{Input impedance} & 16 \text{ k}\Omega \\ \text{Pulse length} & \geq 3 \text{ s} \end{array}$

Output

Output type 1 switch output PNP, NO Rated operating current I_e 200 mA , short-circuit/overload protected

Off-state current I_r \leq 0.01 mA Temperature influence + 0.17 %/K

Ambient conditions

 Ambient temperature
 -25 ... 70 °C (-13 ... 158 °F)

 Storage temperature
 -40 ... 85 °C (-40 ... 185 °F)

 Shock resistance
 30 g , 11 ms period

Vibration resistance 10 ... 55 Hz , Amplitude ± 1 mm

Mechanical specifications

Connection type M8 x 1 connector , 4-pin

Degree of protection IP

Material
Housing Polycarbonate

Transducer epoxy resin/hollow glass sphere mixture; polyurethane foam

max. 0.2 Nm

Installation position any position
Mass 10 g

Tightening torque, fastening screws Compliance with standards and

directives

Standard conformity

Standards EN 60947-5-2:2007 + A1:2012 IEC 60947-5-2:2007 + A1:2012

Approvals and certificates


UL approval cULus Listed, General Purpose
CSA approval cCSAus Listed, General Purpose

CCC approval / marking not required for products rated


≤36 V

www.pepperl-fuchs.com

Dimensions



Electrical Connection



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)

Accessories

UB-PROG4-V31

Programming unit for ultrasonic sensors with Teach-in input at pin 2

OMH-ML7-01

Mounting aid for ML7 and ML8 series, Mounting bracket

V31-GM-2M-PVC

Female cordset, M8, 4-pin, PVC cable

V31-WM-2M-PVC

Female cordset, M8, 4-pin, PVC cable

Description of Sensor Function

The ultrasonic sensor transmits ultrasonic packets in quick succession and responds to their reflection off the detected object. The sensor has a switch output. The switching point is programmable (Teach-In). Objects beyond the taught-in switching point are not detected (background suppression).

Teach-In of Switching Point SP

To teach in a switching point, proceed as follows:

- 1. Connect the sensor and turn on the operating voltage.
- 2. Place the object to be detected at the required distance.
- Connect the teach-in input (ET) to -U_B. This can be done using the pushbutton or the controller.
 The LED will start flashing after 3 seconds to indicate that the sensor is ready to start the teach-in process (*).
- 4. Disconnect the teach-in input (ET) with -U_B. The switching point SP has now been taught in ^(*).
- (*) If no object is detected within the sensing range of the sensor, the sensor will start flashing at a faster rate. The switching point remains unchanged.

Switching characteristics and display LED

unusable	Sensing range	Output	LED
area	Adjustment range		
		-U _B	Off
		+U _B	On
•		Undefined	

= Object position

Safety Note



The use of this device in applications, where the safety of persons depends from the devices function, is not allowed!