



## KDRMA41L1

KDR, 600V, 1/4 HP, 0.50 Motor Amps, 0.80 Max Amps, 3 Phase, Open, Line Inductor, 3% Impedance, UL Listed.

## PRODUCT INFORMATION

SKU: KDRMA41L1. Categories: Input, Line Reactor, KDR.

## SPECIFICATIONS

<b>Rated Voltage</b>	600
<b>Hertz (Hz)</b>	50/60
<b>Horsepower (HP)</b>	0.25
<b>kVAR</b>	0
<b>Phase</b>	3
<b>Max Amps</b>	0.8
<b>UL</b>	UL Listed
<b>Enclosure Type</b>	Open
<b>Watts Loss</b>	3.9
<b>Dimensions</b>	Height: 3.63 in Width: 4.45 in Depth: 1.78 in
<b>Weight</b>	1.2 lbs

Contact TCI for more information or to place an order:  
800-824-8282 | sales@transcoil.com | transcoil.com  
W132 N10611 Grant Drive, Germantown, WI 53022